

## 1/ Integrated T5 LED (Linkable)




LED Fixture

Power Cord

connecting cable (Sell Separately)

1.2M power cord with plug on one end and another male end (Sell Separately)




wire box with female end & on/off switch (Sell Separately)


## 2/ HARDWARE CONTENTS












## 3/ ASSEMBLY INSTRUCTIONS

- 1. Drill two holes at the desired location on the wall (the holes should be near the two ends of the T5 fixture). Then put the roll plugs in the holes.
- 2. Select suitable size of screws and then put the clip on the screw, then screw in both screws and clips into the roll plug.
- 3. Use the switch on the T5 fixture to choose a color temperature before installing.
- 4. Make sure the clips are installed in place tightly. Then click the T5 fixture in the clips.
- 5. Linking options
  - For 0.5ft (150mm)T5 fixture, you can link 26pcs at maximum.
  - For 1ft (300mm)T5 fixture, you can link 16pcs at maximum.
  - For 2ft (600mm)T5 fixture, you can link 9 pcs at maximum.
- 6. If the T5 fixtures are installed on differernt horizontal line.
  - You can use the connecting cable to connect the two T5 fixtures.
  - Make sure everything is connected properly.
  - Put the female end cap at the end of last T5 fixture.
  - Connect the power cord with the male end of first T5 fixture.
  - Then connect with the power.



## 4/ COMPATIBLE DIMMER LIST

Dimmer Brand
Lutron
Levition
Lutron
Lutron
Levition
MACL
Lutron